

How to pair receiver with detector?

Please click this link to see the video:

<https://www.bestguarderonline.com/movieshow.asp?id=11>

Operating Steps:

1. Power on receiver.
2. Press and hold "Reset" button on the back of the product for 6 seconds.
3. While red light is blinking, the receiver will clear all existing paired records.
4. Then Power off the Receiver.
5. Turn on Detector, detector power light will blink for a short period of time.
6. Turn on Receiver, press and hold "Reset" button for 3 sec immediately after detector lights stop blinking, release "Reset" button after "Di" sound. Your alarm is now pairing. (After power on detector, please finish step 6 "Reset" procedure within 10 sec)
7. To test, trigger the detector, the signal indicators (1,2,3,4,5) on receiver should start blinking with sound and vibration.
8. Pairing is completed.

Notice:

- 1) Pair detector with receiver one by one in order. And turn off last one to start next detector pairing. (For Example: Turn off Detector 1, then start to turn on Detector 2 pairing)
- 2) Make sure no unit with a transmitter frequency of 433MHz (for example certain Bait boat) is switched on within an area of 600m when you start to pair.